Sonesse[®] 40 AC Zigbee



The Sonesse® 40 AC Zigbee motor is a connected, bi-directional, quiet 120V/60Hz AC wired motor dedicated to a wide range of interior window coverings. It features a powerful range of lifting capacities (4, 6, and 9 Nm) within a smaller overall footprint to fit narrow window openings.

Compatible end-products



Main functionalities





Easy installation

- Seamless integration to match any interior decor • Thin round head for smooth transition into
- shade and tube profile • Interchangeable head color (white, black, and grey) to match fabric and hardware style or
- color • Recessed interchangeable metal adaptor plate
- compatible with all hardware systems Smaller light gap to minimize light leakage
- Fits small diameter tubes (suitable for an internal diameter of 38mm or more)
- Ideal for narrow windows to maximize viewable area
- UL listed to comply with local building codes and requirements

Easy integration

• Easily integrates with third-party control systems when used with TaHoma® switch

Easy programming and adjustment with TaHoma[®] pro 🕨 Google Play

somfy.

 Allows for quick and easy configuration of motors and operational settings to simplify the installation process

- Installation and programming done directly from the app: intuitive step-by-step programming instructions
- Integrated button on the motor head allows for leaving the network and full reset
- LED feedback for easy troubleshooting
- Acts as a Zigbee[®] mesh network router to extend radio range

Maintenance

• Dedicated maintenance tool, Serv-e- Go (coming in 2024)

Sustainable

• Eco-designed motor with the Act for Green promise by Somfy that provides a PEP Ecopassport Environmental Product Declaration for LEED V4.1 credit

Reliability and services

- Highly secure protocol
- Somfy guality and warranty

Benefits for end users

Comfort, convenience, and privacy

- Convenient solution for glare reduction, natural light management, and privacy via timed schedules and scenes
- Superior quiet performance

Discreet integration and home harmony

- Smaller diameter to maximize viewable window space
- Shorter length to fit smaller windows
- White and thin round head for discreet blending (black and grey as an option)

Easy to use and maintain

- Easily control shades with the TaHoma[®] app
- Get real time feedback on shade positioning via a smartphone or tablet
- Hard-wired, maintenance-free solution

Go hands free with voice control

• Compatible with voice control assistants (with TaHoma® switch and Amazon Alexa, Google Home, or Apple Home)

Sustainable

 Intelligent solar protection ensures improved energy efficiency that reduces CO2 emissions

Safety and reliability

- No hanging cords, provides a child-safe pet friendly solution
- Somfy guality and warranty

Act for Green®

Somfy's voluntary initiative, which aims to reduce the environmental impact of products throughout their life cycle



GREEN

PEP EcoPassport

LEED v4.1 (1 credit) with products having an EPD (Environmental Product Declaration) with a focus on sustainability



TaHoma[®] pro app Scan a unique motor QR code and follow a simple, step-by-step process to configure motor settings

and end limits to save time.

n Android

Google Play

App Store

omio

iOS

Sonesse[®] 40 AC Zigbee

Somfy DESIGNED FOR SILENCE

Item #: 1245920 Sonesse® 40 Zigbee 404S2 with Fast Connector Item #: 1245921 Sonesse® 40 Zigbee 406A2 with Fast Connector Item #: 1245922 Sonesse® 40 Zigbee 409R2 with Fast Connector

Technical data

Voltage Supply	120V/60Hz AC
Index Protection Rating	IP 31 (for indoor use only)
Limit Switch Type	Electronic
Limit Switch Capacity	250 turns
Temperature Working Range	32°F to 140°F (0°C to 60°C)
Insulation Class	Class II
Thermal Protection	4 minutes
Repeatability	+/-4°

6.9 in. (17.5cm) wire length, must not be cut or lengthened. For Antenna greatest RF range, antenna must be out of the rail/tube/cassette.

Dimensions

1.14 in .31 in (29mm) (8mm) 2 mounting holes for self-tapping screws M4 x 8mm (cat #9026094) LED Buttor spaced 1.14" (29mm) apart. ø15in Self-tapping mounting (38mm) screws are included with ╈ each motor. Antenna Power Cable Round Head

Performances

Torque (Nm)	4	6	9
Speed (rpm)	36	24	14
Motor Length (L) in./mm	20.2 in. (514mm)	21.5 in. (545mm)	
Rated Current (Amp)	0.79	1	1
Radio Frequency	2.4 GHz		
Radio Protocol	Zigbee 3.0 / Bluetooth 4.2		
Stand By Consumption (W)	0.5		
Sound Level dB(A)*	42	44	40

*Sound level:

Power Level: according to standards ISO3741 in dB(A) ref 1pW typical value, at nominal torque and nominal speed, without application/end product.

Integrated Motor Plates (sold separately):

L

Fabrication recommendations:

Power Cable

Fast Connector 7.9 in. (20cm)

contact with the basic motor tube.

• Operational noise level is reduced when motor, tube, and mechanical accessories are properly adapted to motorized applications. • Free play must be minimized between the accessories and the end product tube to ensure quiet performance of the motor. • Inside Tube Diameter (ID) > or = 38mm must be respected to prevent

• 400 Series Drive Stop and Screw (#9147894) is recommended to prevent

noise and drive wheel separation from motor shaft.

Cable type: White 2-conductor SVT 2 - AWG 18 : 0.824 mm² /

9025997	Sonesse 40 Motor Plate Rollease R16-24 15.9 x 1.8mm & screws	5
9026000	Sonesse 40 Motor Plate Rollease RBGAL 16 x 3.2mm & screws	↓ ↓ ↓
9025996	Sonesse 30 Motor Plate Rollease 360 R3-R8 10 x 1.8mm and screws	
9025999	Sonesse 30 Motor Plate Acmeda 12mm and screws	A & A &
9026003	Sonesse 30 Motor Plate Rollease Skyline and screws	
9026093	Sonesse 30 Motor Plate M3 x 6mm Philips flat-head plastite screw	<u>I</u>

Optional Head Covers:









Certifications





© Somfy Systems, Inc. • MARCH 2024 All brands, products, and trademarks are the property of their respective owners. A BRAND OF **SOMFY⁹** GROUP